

Baseus倍思

BA03 immersive 3D audio Bluetooth adaptation manual

"Please read this manual carefully before using the product, and please keep it properly"

1. Product appearance

Indicator light

NFC area

Baseus

Multi-function key: Long press: switch the machine key, click: play/pause/answer/hang up, double-click: switch the sound mode

Microphone hole

Volume + key: Single click: Volume increase Long press: Switch to the next song Volume + key: Single click: Volume down Long press: Switch to the previous song

Aluminum alloy back clip

3.5mm headphone jack

Power indicator: All three lights are on: 100%-66.6% power, two lights are on: 66.6%-25% power, one light is on: 25%-0%

Type-C charging hole

2. Product parameters

Brand: Baseus (Baseus)

Product Name: Immersive 3D Audio Bluetooth Adapter

Model: Baseus BA03 Material: ABS + Aluminum Color: Black/White Bluetooth Version: V5.0 Bluetooth Device Name: Baseus BA03 Communication Distance: 10 meters Standby Time: 120 hours

Talk time: 6 hours (70% volume) Listening time: 6 hours (70% volume) Battery capacity: 400mAh Input: DC5V 550mA Rated current consumption: 100mA Charging time: 1 hour Charging interface: Type-C Applicable models: playback equipment with Bluetooth function Accessories: charging cable *1pcs, audio cable *1pcs, manual *1pcs, Warranty card*1pcs, storage bag*1

Three, packing list

1. Bluetooth adapter*1pcs

2. Manual/Warranty card*2pcs

3. Charging cable*1pcs

4. Audio cable*1pcs

5. Storage bag*1pcs

Four, operation method

1. Button definition:

2. Pairing mode: 1) When the Bluetooth is paired for the first time, please control the distance between the Bluetooth adapter and the phone within 1M. 2) When the Bluetooth adapter is off, press and hold the "Multi-function button" for 4 seconds until the white light flashes quickly, at which time the Bluetooth adapter has entered the pairing mode. 3) Turn on the Bluetooth function of the mobile phone, search for Bluetooth devices, select the device model: Baseus BA03, and click Connect. 4) Enter the pairing password "0000" (some mobile phones require password pairing, and some phones do not need password pairing). 5) Please repeat the above operation after the pairing fails, the white light will flash slowly after the pairing is successful. 6) When the user wants to switch the Bluetooth device connection, it needs to enter the switch pairing operation: in the connected state, press and hold the volume "+" and volume "-" keys at the same time for 3S to disconnect the current connection and re-enter the pairing mode, which can be paired to connect to other devices.

3. Call mode: 1) Answer a call: When a call comes in, short press the "MFB" key to answer the call. 2) Hang up the call: During a call, short press the "MFB" key to hang up the call. 3) Rejecting a call: When a call comes in, press and hold the "MFB" button for 2 seconds to reject the call. 4) Audio switching: During a call, press and hold the "MFB" button for 1 second to transfer the voice from Bluetooth to the phone, and then long press to switch back to Bluetooth. 5) Multi-party call: When phone 1 comes in, tap the "MFB" button once to answer phone 1, when phone 2 comes in, double-click the "MFB" button once to keep the call on phone 1 and answer the call on phone 2, then double click on phone 1 switch with phone 2, short press to hang up call 1, long press to hang up call 2.

Five, frequently asked questions:

1) Why can't my product be turned on? Answer: For the first use, make sure the headset is fully charged. If there is no power, the product will not turn on.

2) There is no sound from the earphone when playing songs after linking? Answer: Check whether the playback device and the mobile phone, Bluetooth adapter and headset have established a valid connection. If the audio device fails to connect normally, please reconnect. At the same time adjust the volume of the mobile phone or Bluetooth adapter to a suitable volume level. 3) Why is the Bluetooth connection unstable? How far is the distance between the mobile phone and the Bluetooth adapter? Answer: Please make sure that the effective distance between the mobile phone and the Bluetooth adapter is 10 meters. Generally speaking, if there is no obstacle between the mobile phone and the Bluetooth adapter, the Bluetooth receiving distance is better and more stable. Please make sure that there are no wireless interfering devices and wifi devices nearby. interference. 4) Can I use the Bluetooth ear adapter when charging? Answer: No, the headset cannot be used while charging.

6. Declaration of Toxic and Hazardous Substances in Electronic Information Products

Part name PCB	Toxic and harmful substances or elements				
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr(VI))	Polybrominated biphenyls (PBBs) / Polybrominated diphenyl ethers (PBDEs)
Battery housing	XX	0.0000	0.0000	0.0000	0.0000
wire assembly					
Accessories	OK				
	0				

This table is compiled in accordance with the provisions of SJ/T 11364 0. It means that the content of this toxic and hazardous substance in all homogeneous materials of this part is below the limit requirement of GB/T 26572. X: Indicates that the content of the toxic and hazardous substance in at least one of the homogeneous materials of the part exceeds the limit requirement of GB/T 26572. The information provided in this form is based on the data provided by the supplier and the test results that meet the ROHS environmental protection requirements. At the current level of technology, the use of all toxic and hazardous substances or elements is controlled to the bottom line. But in line with the exemption of the EU ROHS directive. The environmental protection period is 5 years.

Seven, product safety information

Please read all instructions and warnings before using this product. Irregular use will cause damage to the product.

1) High volume may affect hearing. For traffic safety, do not use earphones while driving or cycling. 2) Children should use this device under adult supervision. This product is not a toy. 3) The product contains a battery, please do not expose it to sunlight, fire or similar overheating environment, the input voltage of the charger port cannot exceed 5V for charging. During the charging process, when there is overvoltage, overcurrent or overtemperature, it will automatically stop Charge to avoid injury, when it returns to normal state, charge continues. 4) Please charge your headset regularly (recommended once a month) to maintain its long service life.

Tips:

* Improper use of the product may easily cause damage to the product itself or may endanger personal and

* If the personal and property damages caused by consumers violating the product manual or improper use or warnings will bear all the consequences, the company will not bear any legal responsibility.

Brand name: Baseus Producer: Shenzhen Shishang Changheng Technology Co., Ltd. Address: Room 03, 6th Floor, Building 3, Yunk Smart Park, Fada Road, Bantian Street, Longgang District, Shenzhen

Producer: Shenzhen Jinhui Electronics Co., Ltd. Manufacturer Address: 3rd Floor, Bihua Science and Technology Park, Shanggang Community, Guanlan Street, Longhua New District, Shenzhen Executive Standard: GB8898-2011

CMIT ID: 2015CP9939

Phone: +86 755-62433603 Website: www.baseus.com

Baseus

BA03 Immersive Virtual 3D Bluetooth Receiver Instruction

Please read this instructions completely and keep it properly

1.Product appearance

Indicator light

NFC Area

Baseus

Multi-function key: Long press: Start-up/ Shutdown Click/Play/pause/answer/hang up Double-click: Switching of sound effect mode

Microphone hole

Volume+key: Click-Volume Up Long press-switch to the next song Volume-key: Click-Volume Down Long press-switch to the previous song

Aluminium alloy back clamp

3.5mm Earphone jack

Battery level indicator: One light on: 25%-0% of the power Two lights on: 66.6%-25% of the power Three lights on: 100%-66.6% of the power

Type-C Charging hole

2.Product Parameter

Brand: Baseus Product Name: Immersive Virtual 3D Wireless Receiver Model: Baseus BA03 Material: ABS+ Aluminum alloy Color: Black/White Version: V5.0 Device name: Baseus BA03 Communication distance: 10 meters Standby time: 120 hours

Call time: 6 hours(70% of the volume) Music time: 6 hours(70% of the volume) Battery capacity: 400mAh Input: DC5V 550mA Rated current consumption: 100mA Charging time: 1 hours Charge interface: Type-C Suitable for: Compatible with all wireless devices-Accessories: Charging cable*1pcs,Audio cable*1pcs,User manual*1pcs , Warranty card*1pcs,Storage bag *1pcs.

3.Packing list

1. Bluetooth Receiver *1pcs

2. User manual/ Warranty card*2pcs

3. Charging cable*1pcs

4. Audio cable*1pcs

5. Storage bag*1pcs

4.Operating method

1.Key Definition:

1) Multi-function button (MFB): Start-up: Press the multi-function button for about 2 seconds Shutdown: long press the multi-function button for about 4 seconds Play/pause/answer/hang up: short press the multi-function button for 1 second Switching of sound effect mode: Double-click the multi-function button

2) Volume + key: Click: Volume Up Long press for 3 seconds: switch to the previous song 3) Volume One key: Click: Volume Down Long press: switch to the next song 4) NFC pairing connection: NFC is turned on for Android device and the screen is unlocked. Tap NFC detection area for quick pairing connection: double-click the multi-function button

Pairing Mode:

1) When pairing Bluetooth for the first time, please make sure the distance between Bluetooth adapter and mobile phone within 1M.

2) When the Bluetooth adapter is turned off, long press the "multi-function button" for 4 seconds until the white light flashes quickly. At this time, the Bluetooth adapter has entered the pairing mode. 3) Turn on the Bluetooth of the mobile phone, search for Bluetooth devices, and select the device model: Baseus BA03, and click Connect.

4) Enter the pairing password "0000" (some mobile phones require password for pairing, while some not). 5) Please repeat the above operation in case the pairing 2 short press to hang up call 1 and long press to hang up call 2. 1) Multi-function button (MFB) Power on Long press the multi-function button for about 2 seconds, power off Long press the multi-function button for about 4 seconds, the white light will flash slowly after the pairing succeeds. 6) When the user wants to switch the Bluetooth device connection, he or she needs to switch pairing: when the device is connected, long press both the volume "+" and volume "-" keys for 3s at the same time to disconnect the current connection and re-enter the pairing mode, so that other devices can be paired and connected.

3. Talk mode: 1) Answer a call: When there is an incoming call, press once the "MFB" to answer the call. 2) Hang up a call: When calling, press once the "MFB" to hang up the call. 3) Reject a call: When there is an incoming call, Press and hold the "MFB" for 2s to reject the call. 4) Radial Audio switch: During voice call, press and hold MFB switch for 1S from headphone to smartphone, do the same switch back to headphone.

5) Multiparty Call: When there is an incoming call, press once the "MFB" to answer the call 1. When the other call 2 is coming, press once to answer call 2, double click "MFB" key to switch between call 1 and call 2.

5.FAQs:

1) Why product cannot be turned on? Answer: When using your product at the first time, please check and make sure the product battery is fully charged. If the battery runs out of power, your earphone may not be turned on.

2) The earphone is silent during playback? Answer: Check for a valid connection between the mobile phone, wireless adapter and your earphone. If the device is not properly connected, please reconnect it. Meanwhile, please also adjust the volume on mobile phone or your earphone to a proper level.

3) Why the wireless connection is unstable, and how far should my mobile phone be kept from wireless adapter? Answer: Please make sure that your mobile phone is kept within 10m effective distance from your wireless adapter. Usually if there is no obstruction between your mobile phone and your wireless adapter, then the connection distance can be better. Please make sure that there is not any interference from wireless devices and WIFI devices nearby.

4) May I use my wireless adapter while it is being charged? Answer: No, you can not use your wireless adapter while it is being charged.

6.Declaration on Toxic or hazardous substances and elements contained in electronic products

Part Description	Toxic or hazardous substances and elements				
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr(VI))	Polybrominated biphenyls (PBBs) / Polybrominated diphenyl ethers (PBDEs)
PCB Battery	XX	0.0000	0.0000	0.0000	0.0000
Housing Cable					
Accessories	OK				
	0				

This form is prepared in accordance with the provisions of SJ/T 11364 0. Indicates that contents of the toxic and hazardous substances in all homogeneous materials are below the limit requirements specified by GB/T 26572 standard. X: Indicates that contents of the toxic and hazardous substances exceed the limit requirements specified in GB/T 26572 standard in at least one homogeneous material of the part. The information provided in this form is based on the data provided by the supplier and in line with the detection result of ROHS environmental requirements. At the current level of technology, use of all toxic and hazardous substances or elements is controlled to the bottom line, but immunity of EU ROHS directive is followed. Environmental protection limit lasts 5 years.

7.Product Safety Information

Please read all instructions and warnings before using this product. Improper use of the product will cause damage to the product.

1) High volume may affect hearing. For traffic safety, do not use headphones while driving or cycling.

2) Supervise children when using the equipment. The product is not a toy.

3) The battery is included in the product. Please do not expose it to sunlight, fire or similar overheating. The input voltage of the charger port should not exceed 5V. During charging, when overvoltage, over-current or over-temperature occurs, the charging will stop automatically to avoid injury. When returning to normal state, charging will continue.

4) Please charge your headset regularly (suggested once a month) to maintain its long life.

Tips:

* Improper use of the product may easily cause damage to the product itself or may endanger the safety of people and property.

* If the personal and property damage caused by improper use or warning of the product in violation of the product instruction, consumer will bear all consequences. Our company will not bear any legal responsibility.

Shenzhen Times Innovation Technology Co., Ltd. Address: Room 03, 6/F, Building 3, WINLEAD, Fada Road, Bantian Street, Longgang District, Shenzhen, China TEL: +86 755-82433603 Hotline: 4000-712-711 Baseus design/Made in China